

CISCO · CATALYST 9000 SWITCH POWER SUPPLY

PWR-C1-1900WAC-P

1900W AC PSU · Catalyst 9300 C1 · Platinum Rated

New, factory-sealed · 3-year LSCare warranty · Ships from Hong Kong and US stock



Product Model	PWR-C1-1900WAC-P
Category	Catalyst 9000 Switch Power Supply
Condition	New, factory-sealed
Warranty	3-year LSCare warranty
Supplier	Layer23-Switch · www.layer23-switch.com



Scan for price and stock

200+

Countries Served

18,000+

Customers Worldwide

US\$9M+

Ready-Stock Inventory

3-Year

Warranty



CISCO · CATALYST 9000 SWITCH POWER SUPPLY

PWR-C1-1900WAC-P

1900W AC PSU · Catalyst 9300 C1 · Platinum Rated

The PWR-C1-1900WAC-P is a Cisco Catalyst 9300 Series 1900W AC Platinum power supply module for Catalyst 9300, Catalyst 9300L, and Catalyst 9300X switch power-supply bays. It supports high-output PoE power plans and spare PSU replacement for C1 power-supply systems, with 1900W output at 230V nominal input or 1500W output at 115V nominal input.

New, factory-sealed · 3-year LSCare warranty · 14-day returns · Cisco SN check before shipment

Specifications

Product ID	PWR-C1-1900WAC-P	Product type	1900W AC Platinum certified power supply module
Efficiency class	Platinum certified	Supported switch families	Catalyst 9300, Catalyst 9300L, and Catalyst 9300X
C9300LM support boundary	PWR-C1 supplies are not used with C9300LM switches	Maximum output at 230V input	1900W
Maximum output at 115V input	1500W	230V input range	200 to 240 VAC autoranging, 55 to 60 Hz
115V input range	115 to 127 VAC autoranging, 50 to 60 Hz	Input current at 230V	Maximum 12A
Input current at 115V	Maximum 16A	Output rating at 1900W	-56V at 33.92A
Output rating at 1500W	-56V at 26.78A	Total input BTU at 1900W	6899 BTU/hr, 2022W
Total input BTU at 1500W	5565 BTU/hr, 1631W	Total output BTU at 230V	6483 BTU/hr
Total output BTU at 115V	5118 BTU/hr	Unit weight	3.4 lb (1.5 kg)
Dimensions	1.58 x 3.25 x 13.7 in. (40.1 x 82.55 x 348.2 mm)	Power-supply slots	Two internal Catalyst 9300 power-supply slots
Slot population rule	Use a second PSU or blank cover in the unused slot	Installation depth note	1900W module extends 1.5 in. from the switch rear panel
Status LEDs	AC OK and PS OK LEDs indicate input and output status	Hot-swap note	Hot-swap only when the remaining power budget supports the load
Power cord planning	Use Cisco-listed suitable AC power cord options for PWR-C1-1900WAC-P		

Get Price and Availability for PWR-C1-1900WAC-P

New, factory-sealed units with a 3-year warranty. Our sales team quotes within one business day, and in-stock orders ship within one business day of payment from our Hong Kong and US warehouses.

[Request a Quote](#)

[View Product Page](#)



Email sales@layer23-switch.com WhatsApp [+86 171 8118 9993](https://wa.me/8617181189993) WeChat [layer23-switch](https://www.whatsapp.com/channel/00299a60000000000000000000000000) Telegram [@layer23_switch](https://t.me/layer23_switch)

Address 2810 North Church Street, Suite 89727, Wilmington, DE 19802, USA

Cisco and Cisco product names are trademarks of Cisco Systems, Inc. Specifications are summarized from manufacturer documentation for reference; confirm the exact configuration with Layer23-Switch before ordering. Revised October 2026.

LAYER23-SWITCH